

Data Sheet

We make sure



AMILO Notebook Pi 3525

The perfect all-round notebook

Issue July 2008

Version 1

Pages 5

The AMILO Notebook P series combines versatile performance, great technology and a fascinating design.

Processor technology

- Latest Intel® Centrino® 2 processor technology with Intel® Core™ 2 Duo processor for high-definition digital entertainment experience, blistering performance, longer-lasting battery life and the new wireless standard for connectivity

Operating System

- Windows Vista® Home Premium

Mobility

- Standard 15.4-inch form-factor that fits in almost every bag
- Optional with integrated draft-n Intel® WiFi Link 5100 AGN to go online when and wherever you want

Entertainment and Multimedia

- The integrated AMILOcam with low-light technology for great video-quality even in low-light conditions and the built-in array microphone are perfect for Internet telephoning (VoIP) and video chats
- LCD WXGA display with BrilliantView technology for vivid colors, amazing sharpness and impressive contrast
- Enjoy your favorite Hollywood blockbuster on an external display via DVI-I (with HDCP support)

More convenience thanks to

- The spill-proof keyboard that protects your notebook against accidentally spilt liquids
- The silent mode function that causes a noticeable reduction in fan noise
- The built-in DVD drive to store and secure data comfortably on the move



Fujitsu Siemens Computers recommends Windows Vista® Home Premium

Operating system and Recovery

Operating system	Genuine Windows Vista® Home Premium (32-bit version)
Fujitsu Siemens Computers Recovery Program	Backup and restore the original status of the hard disk and create system restore disks
	or individual recovery media on CD or DVD are included

Architecture

System architecture	Intel® Centrino® 2 processor technology (optional) ¹
Chipset	Intel® GM45 + ICH9M
Processors¹	
Intel® Core™2 Duo processors	P7350 (2.0 GHz, 1066MHz FSB, 3MB L2 cache) P8400 (2.26 GHz, 1066MHz FSB, 3MB L2 cache) P8600 (2.4 GHz, 1066MHz FSB, 3MB L2 cache)

Memory

Memory speed	2 SO-DIMM memory slots (no memory on board)
Memory type	800 MHz
Memory modules	DDR 2 RAM
Max. memory size ^{1,2}	1024 or 2048 MB
	4096 MB

Drives**Hard disk drive**

HDD type	SATA
HDD size	2.5-inch
HDD speed	5400 rpm
HDD cache	8 MB
HDD capacity ¹	160, 250 or 320 GB

Optical disc drive (built-in)

ODD type	SATA
ODD technology	SuperMulti-format DVD burner with dual double layer (DL) support
ODD read speed	CD-ROM 24x, DVD-ROM 8x
ODD write speed	CD-R 24x, CD-RW 16x, DVD+R 8x, DVD-R 8x, DVD+RW 8x, DVD-RW 6x, DVD+R DL (8.5 GB) 4x, DVD-R DL (8.5 GB) 4x, DVD-RAM 5x

Display

Display type	BrilliantView LCD
Display size	15.4-inch
Display resolution (intern)	1280 x 800 pixels
Display resolution (extern)	1920 x 1200 pixels
Resolution type	WXGA
Reaction time	16 ms
Brightness (typ.)	200 NIT
Contrast (typ.)	400 : 1
Compliance with standards	ISO 13406-2 class II

Graphics

Dedicated graphics (full name)	-
Dedicated video memory	-
Onboard graphics chip	Mobile Intel® Graphics Media Accelerator 4500MHD
Shared video memory ³	Up to 256 MB shared memory ³
3D Benchmark 2006	840 points ⁴
Graphic features	<ul style="list-style-type: none"> ■ DirectX® 10 support ■ Supporting full HD video experience

Fujitsu Siemens Computers recommends Windows Vista® Home Premium

Interfaces

Video	1x DVI-I
Audio	1x line in, 1x microphone in, 1x line out / headphone out combined with S/PDIF out
Network	1x LAN (RJ-45)
Data	1x eSATA combined with USB, 2x USB 2.0 1x ExpressCard slot (54 / 34 mm) 1x 15-in-1 card reader ⁵ SD, miniSD, MicroSD, SDHC MS, MS-Duo MMC, RS-MMC, MMC-Micro MSPRO, MS-PRO Duo, MS-Pro HG, MS-Pro HG Duo, M2 xD picture card
Power supply	1x DC-in

Communication

Integrated Bluetooth®	-
LAN (Local Area Network)	10 / 100 Mbps
Built-in WLAN (Wireless Local Area Network)	Yes
WLAN brand name	Intel® WiFi Link 5100 AGN
WLAN type ¹	draft-n 802.11a/g/n
WLAN max. data rate	Up to 300 Mbps
WLAN encryption	WEP, WPA and WPA2
For use in	BE, CH, DK, DE, EE, FI, FR, EL, IE, IS, IT, LI, LV, LT, LU, MT, NL, NO, PL, AT, PT, SE, SK, ES, CZ, HU, UK, CY
Option ¹	
WLAN type	802.11b/g
WLAN max. data rate	Up to 54 Mbps
WLAN encryption	WEP, WPA and WPA2
For use in	BE, CH, DK, DE, EE, FI, FR, EL, IE, IS, IT, LI, LV, LT, LU, MT, NL, NO, PL, AT, PT, SE, SK, ES, CZ, HU, UK, CY

Multimedia**Audio**

Audio chip	Support of HD audio for S/PDIF output with up to 7.1 channels
Speakers	Realtek ALC662
Microphone	2x built-in speakers (1.5 W each)
Subwoofer	Built-in array microphone
Input device	-
	Volume control via function key combination

AMILOcam

Image sensor	VGA webcam
Frames per second	30 ⁶
Features	<ul style="list-style-type: none"> ■ Auto focus ■ Automatic brightness adjustment with status LED (blue: on, red: streaming / application on) ■ Low-light technology for great video-quality even in dark surrounding

Input devices / Control buttons

Power button	Located left of the keyboard
Keyboard	Spill-proof keyboard with 85 keys
Touchpad	Hidden touchpad, with left and right mouse button, touchpad disable function via function key combination (Fn+F6)
Multimedia keys	Located on top of the keyboard to launch the following applications: <ul style="list-style-type: none"> ■ Silent mode (reduce noise level / fan speed, by reducing the CPU performance, office applications, Internet and DVD playback are not affected) ■ DVD playback ■ Internet browser

Fujitsu Siemens Computers recommends Windows Vista® Home Premium

Hot keys	<p>The following hot keys or key combinations are available</p> <ul style="list-style-type: none"> ■ Fn+F1 WLAN on / off ■ Fn+F3 Mute on / off ■ Fn+F4 Volume down ■ Fn+F5 Volume up ■ Fn+F6 Touchpad on / off ■ Fn+F7 AMILOcam on / off ■ Fn+F8 Brightness down ■ Fn+F9 Brightness up ■ Fn+F10 Display switch ■ Fn+F11 Silent mode ■ Fn+F12 Suspend
Status indicators	<p>The notebook has 3 status icons:</p> <ul style="list-style-type: none"> ■ Power status (& suspend) Blue (always on): on; Blue blinking: stand by, None: off ■ WLAN Blue: on; None: off ■ Battery charge Blue (always on): full, Blue blinking: charging; Red blinking: < 10 % capacity
Security Supervisor and user password Kensington lock Lid switch (hidden)	Yes Yes Yes
ACPI functions	<p>ACPI 3.0 compliant for Vista requirement</p> <ul style="list-style-type: none"> ■ S1 LCD off ■ S3 save to RAM ■ S4 save to disk ■ S5 soft off
Power System Battery⁷ Battery type ¹	<p>Lithium-Ion battery 6 cells, 10.8 V / 2200 mAh (cell) / 4400 mAh (pack) or 6 cells, 11.1 V / 2400 mAh (cell) / 4800 mAh (pack)</p>
Battery runtime (idle mode) ⁸ Battery runtime (DVD Playback) ⁹ Battery charging time (idle mode) ¹⁰ Battery charging time (DVD playback) ¹¹ Battery charging time (off mode)	<p>Up to 3:45 hours Up to 1:45 hours Up to 1:40 hours (charging 90%) Up to 2:20 hours (charging 90%) Up to 2:00 hours (charging 90%)</p>
AC Adapter Wide Range AC adapter Output	<p>Dynamic charge supported, ACPI 2.0 supported 110 - 240 V AC, 50 - 60 Hz 65 W with 20 V DC, 3.25 A</p>
Energy consumption S0 (idle mode) S0 (max. active mode) ¹² S3 (stand by / energy saving mode) S4 (hibernate) S5 (off mode)	<p>19 W 48.6 W 12.3 W 0.8 W 0.7 W</p>
Noise emission Idle mode ¹³ Maximum active mode ¹⁴	<p>19 dBA (silent mode off) 28 dBA (silent mode off)</p>
Operating conditions Operational AC input	<p>5 °C to 35 °C (ambient temperature) 10 % to 90 % relative humidity, non-condensing 100 - 240 V, 50 - 60 Hz</p>
Dimensions and weight W x D x H Weight	<p>358 x 256 x 37.0 (front) / 41.0 (back) mm 2.9 kg¹⁵</p>

Fujitsu Siemens Computers recommends Windows Vista® Home Premium

Certifications	GOST (WLAN) CE Marking R&TTE (WLAN)
Warranty	Country specific terms
Operational Software	
Home office	Microsoft® Works Microsoft® Office Home and Student Trial Adobe Reader Windows Mail (within Vista operating system) Windows Calendar (within Vista operating system)
Multimedia	Nero Essentials S (CD / DVD write software) Vista DVD Playback Pack (DVD playback software) Windows Media Player (within Vista operating system) Optional ¹ : Windows Media Center (within Windows Vista® Home Premium operating system)
Internet	Microsoft® Internet Explorer Country specific Internet provider
Security	Norman security software solution
Accessories	
Included	AC adapter 65 W First Battery (6 cells battery)
Manuals	Manual (on hard disk), quick start guide, safety guide, warranty guide, recovery guide
Drivers	Updates downloadable at http://www.fujitsu-siemens.com

¹ Depending on exact configuration. Please check at your local retailer² DISCLAIMER: Up to 1 GB may not be available with 32-bit operating systems due to system resource requirements if system is preinstalled with 4096 MB RAM³ Shared video memory size may vary depending on configuration. Used video memory size depends on Microsoft® Windows Vista® memory management

- 1024 MB system memory enables up to 256 MB static and shared memory
- 2048 MB system memory enables up to 256 MB static and shared memory
- 3072 MB system memory enables up to 256 MB static and shared memory
- 4096 MB system memory enables up to 256 MB static and shared memory

⁴ Configuration for measurement: Intel® Core™2 Duo T9400 processor, 4 GB RAM, 250 GB HDD; display resolution: 1280 x 1024⁵ An adapter is needed for the following card formats: RS-MMC, MMC-Micro, miniSD, MicroSD, SDHC, MS-Duo, MS-PRO Duo, MS-Pro HG, MS-Pro HG Duo, M2⁶ AMILOcam frame rate can vary significantly depending on the used software application.⁷ DISCLAIMER: Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Recharge time varies depending on usage. The recharge capacity may decrease after some months so that the battery lifetime as well as operating time can not be assured for the whole lifetime of the notebook⁸ Tested with Battery Mark 4.0.1 ("power saver mode")⁹ DVD playback tested with Vista DVD playback¹⁰ Tested with BatteryMon, V2.0 Build:1007¹¹ DVD playback tested with Vista DVD playback¹² Tested with 3DMark06¹³ Tested with idle mode (according to ISO 7779:2001 Nr. C.15.3.1) noise emission values according to ISO 9296 at operator position¹⁴ Tested with HDD stress test and CPU stress test at approx. 90 % CPU load, no ODD load, noise emission values according to ISO 9296 at operator position¹⁵ Weight may vary depending on actual configuration

The configuration described in this document is generic only and non-binding. For the exact configuration of your AMILO, please contact your licensed dealer.